



Vodafone Terminal Capability Definition

Appendix B Utilities TCD – Memory Dial Specification

Version: 9.0.0

Owner: Rob Mitchell
Authors: Osamu Otaka

Table 2.8.5-1 Memory Dial

Keywords	Supplemental Explanation
MEMORY:* (MEMORY: is single byte. MEMORY is case insensitive)	<p>If a keyword is identified in the text, it will be a character set to be set to the memo area.</p> <ul style="list-style-type: none"> * shall be zero or more continuous ASCII code. (Shift_JIS-compliant handsets shall comply with Shift_JIS.) The end of character set shall require the line feed code (CR/LF). The same shall apply to zero characters.
NAME1:* (NAME1: is single byte. NAME1 is case insensitive	<p>If a keyword is identified in the text, it will be a character set to be set to the name of a contact.</p> <ul style="list-style-type: none"> * shall be zero or more continuous ASCII code. (Shift_JIS-compliant handsets shall comply with Shift_JIS.) The end of character set shall require the line feed code (CR/LF). The same shall apply to zero characters.
NAME2:* (NAME2: is single byte NAME is case insensitive	<p>If a keyword is identified in the text, it will be a character set to be set to the how-to-read area of a contact.</p> <ul style="list-style-type: none"> * shall be zero or more continuous ASCII code. (Shift_JIS-compliant handsets shall comply with Shift_JIS.) The end of character set shall require the line feed code (CR/LF). The same shall apply to zero characters.
MAIL1:*@* MAIL2:*@* MAIL3:*@* (MAILx: is single byte MAIL is case insensitive	<p>If a keyword is identified in the text, it will be a character set to be set to the E-mail address of a contact.</p> <ul style="list-style-type: none"> * shall be one or more continuous ASCII alphanumeric MAIL1 is to be set as the first e-mail address in principle. MAIL2 is to be set as the second e-mail address in principle. MAIL3 is to be set as the third e-mail address in principle. The end of character set shall always require the line feed code (CR/LF).
TEL1:* TEL2:* TEL3:* (TELx: is single byte TEL is case insensitive	<p>If a keyword is identified in the text, it will be a character set to be set to the phone number of a contact.</p> <ul style="list-style-type: none"> * shall be one or more continuous ASCII number (0-9) and #,* Shift_JIS-compliant handsets shall comply with Shift_JIS (Double-byte number) TEL1 is to be set as the first phone number in principle. TEL2 is to be set as the second phone number in principle. TEL3 is to be set as the third phone number in principle. The end of character set shall require the line feed code (CR/LF).